






How do I navigate?










- ← **Roll the trackwheel** to move the cursor and highlight items on the screen.
- ← **Click (press) the trackwheel** to open the menu or select items.
- ← **Press the Escape button** to exit a screen, cancel an action, or go back one page in the browser.

Shortcuts












Phone

- Open the phone screen Press the **Phone** button
- End a call Hold the **Escape** button
- Turn on or off mute during a call Press the **Phone** button
- Change the volume during a call Roll the trackwheel
- Dial a letter in a phone number Hold  + Press the letter
- Call a voice mail access number Hold 
- Assign speed dial to a selected contact Hold an unassigned letter key > Click **OK**.
- Recall the last phone number dialed Press  twice.
- Mute a call using a headset Press the headset button
- End a call using a headset Hold the headset button

Browser






- Go back one page Press the **Escape** button
- Exit the browser Hold the **Escape** button
- Search for a word on a page Press 
- Open a selected link Press 
- Switch between normal and full-screen view Press 
- Go down one page Press 
- Go up one page Press  + 
- Go to a specific web page Press 

Message list

- Open a selected message Press 
- Compose new message Press 
- Reply to sender Press 
- Reply to all Press 
- Forward message Press 
- Go to messages from the next day Press 
- Go to the messages from the previous day Press 
- Go to the next unread message Press 
- File a message Press 
- View sent messages Press  + 
- View received messages Press  + 

Calendar






For these shortcuts to work in Day view, in the calendar options, set the **Enable Quick Entry** field to **No**.

- Go to the next day, week, or month Press 
- Go to the previous day, week, or month Press 
- Schedule an appointment Press 
- Move the cursor horizontally in week view Hold  + Roll the trackwheel
- Move the cursor vertically in month view Hold  + Roll the trackwheel

Note: The arrangement of letters on your device keyboard might vary slightly from the depictions on this document.










Navigating screens




- Lock the device/keyboard** Click **Keyboard Lock** (set a password for added security)
- Unlock the device/keyboard** Double-click the trackwheel
- Move the cursor vertically/horizontally** Roll the trackwheel/Press  + Roll the trackwheel
- Return to the previous screen** Press the **Escape** button
- Click an item** Highlight the item > Click the trackwheel
- Select multiple items** Hold  + Roll the trackwheel
- Switch between programs** Hold  + Press the **Escape** button
- Go to the top of a screen** Press 
- Go to the bottom of a screen** Press 
- Turn on/off the device** Hold the **Power** button

Typing and editing



- Capitalize a letter** Hold the letter
- Insert a period** Press  twice
- Type the alternate character on a key** Press  + the key
- Insert a symbol** Press 
- Insert an accented character** Hold a letter + Roll the trackwheel
- Select text** Press  > Roll the trackwheel
- Select characters** Hold  > Roll the trackwheel
- Copy selected text** Press  + Click the trackwheel or Click the trackwheel > Click **Copy**
- Cut selected text** Press  +  or Click the trackwheel > Click **Cut**
- Paste selected text** Press  + Click the trackwheel or Click the trackwheel > Click **Paste**
- Cancel a selection** Press the **Escape** button

Fields




Press  to change the value in a field.

Press  to view all the values that are available in the selected field.

On an option screen, you can also select an option and click the trackwheel. Click **Change Option**. Click a value.

Menus



Click the trackwheel to view the menu.

On the menu, click standard menu items such as **New**, **View**, **Edit**, **Delete**, **Save**, **Options**, and **Help**. Additional menu items might appear depending on the item you have selected.

Programs

Explore the many useful programs that your BlackBerry® device has to offer. Here are a few to get you started.



Click **Messages** to view the messages list, compose new messages, and set options for email messages.



Click **Browser** to visit web pages, browse for programs and ring tones and set browser options. Your device might have more than one browser.



Click **Profiles** to set and edit ring tone profiles or to manage downloaded ring tones.



Click **Options** to find the main list of device options, Bluetooth® settings, and wireless settings.



Additional programs appear on the home screen, including the task list, memos list, calculator, alarm, pictures list, help, and more!

Status indicators

full battery power

voice mail message

placed call

filed message

low battery power

Bluetooth radio on

missed call

message includes attachment

charging

Bluetooth connected

received call

SMS message

roaming

Number mode on

sent message

MMS message

Home zone

Shift mode on

message sending

system busy

receiving data

Alt mode on

message not sent

transmitting data

saved web page

read message

service book waiting

alarm set

unread message

Wireless network coverage

You must connect to the wireless network to begin using many device features. To connect to or disconnect from the wireless network, click **Turn Wireless On/Turn Wireless Off**.

Indicators on the Home screen show the wireless coverage level for the area in which you are using your device. A low level of wireless coverage might limit the use of some device features, as shown in the chart below.

Full wireless coverage	
No wireless coverage	
Wireless is turned off	
Emergency calls only	

	GPRS	gprs	GSM
Emergency calls	●	●	●
SMS messages	●	●	●
Phone	●	●	●
MMS messages*	●		
Email and PIN	●		
Browser	●		

*MMS (Multimedia Messaging Service) subject to availability. Contact your service provider for more information.

Contents

Welcome to BlackBerry!	3	Send MMS (multimedia) messages	15
Setting up your device	5	Add contacts	16
Insert the SIM card	5	Add SIM card contacts to your address book	16
Insert the battery	5	Go to web pages	16
Charge the battery	5	Set a device password	16
Connect to the wireless network	6	Lock and unlock the device	16
		Set the date and time	17
Choosing your email setup option	7	Enable profiles	17
BlackBerry Internet Service option	7	Turn on or off the Bluetooth radio	17
BlackBerry Enterprise Server option	7	Pair with another Bluetooth-enabled device	17
		Find help with other features	17
Setting up for email using BlackBerry Internet Service	9	Frequently asked questions	19
Create an account	9	BlackBerry Internet Service - frequently asked questions	21
Log in to your account	10		
Receive messages from other email accounts	10		
Set account options	11		
Install the BlackBerry Desktop Software	11		
Setting up for email using BlackBerry Enterprise Server	13		
Use enterprise activation	13		
Use the BlackBerry Desktop Software	13		
How do I...	15		
Make phone calls	15		
Send email messages	15		
Send PIN messages	15		
Send SMS (text) messages	15		

Welcome to BlackBerry!

Whether you plan to use your BlackBerry® device for business or personal productivity, you have made an excellent choice! With powerful push-messaging, voice, web, and organizer features, BlackBerry is the all-in-one solution that is designed to keep you connected to the people, data, and resources that you need every day.

To begin using your BlackBerry device, you must set up and turn on the device, connect to the wireless network, and set up your supported email account. You can also choose to install the BlackBerry® Desktop Software so that you can connect your device to your computer for data synchronization and charging.

Take a moment to read this guide as well as any documents provided by your service provider. These resources provide important setup information and are designed to help you get the most from your BlackBerry device! Additional resources are listed in the back of this guide.


Setting up your device

Insert the SIM card


Your SIM card contains important information about your wireless service. Your SIM card might be inserted already.

Warning: Turn off your device before you insert or remove the SIM card. Do not scratch, bend, or expose the SIM card to static electricity or wet conditions.

1. Press the battery cover release button.



2. Slide off the battery cover.
3. If the battery is inserted, remove it.
4. Slide the SIM card holder toward its hinge to unlock it.
5. Lift the SIM card holder.
6. Insert the SIM card into the holder so that the notches align.




7. Close the SIM card holder.
8. Slide the SIM card holder away from its hinges to lock it.

Insert the battery

Warning: Use only the battery that Research In Motion® specifies for use with your device. See the Safety and Product Information booklet that accompanied your device for more information about using the battery safely.


1. Press the battery cover release button.
2. Slide off the battery cover.
3. Insert the battery so that the connectors on the battery align with the connectors on your device.




4. Replace the battery cover.
5. If the battery is charged, your device turns on and the confirm date and time dialog box appears.
 - If the date and time are incorrect, click **Edit**. See "Set the date and time" on page 17 for more information.
 - If the date and time are correct, click **OK**.

Charge the battery

1. Connect the small end of the USB cable to your device.



2. If required, slide the plug blade attachment into the power adapter.



3. Plug the power adapter into a power outlet.
4. Charge the battery to full power.

Note: If you install the BlackBerry Desktop Software, you can charge your device by connecting it to your computer. See "Can I charge my device by connecting it to my computer?" on page 19 for more information.

Connect to the wireless network

On the device, if the power is off, press the **Power** button. Your device should connect to the wireless network automatically.

To connect to the wireless network successfully, your wireless service must be active, and you must be in a wireless network coverage area. See the wireless network coverage chart on the inside front cover of this guide for more information.

When your device is not connected to the wireless network, you can continue to use features that do not require a connection to the wireless network. For example, you can type and save draft email messages, manage tasks, or use the calculator.

Note: If you use BlackBerry Internet Service, the account setup process might begin automatically the first time that your device connects to the wireless network. See "Setting up for email using BlackBerry Internet Service" on page 9 for more information.

Choosing your email setup option

To begin sending and receiving email messages on your BlackBerry device, you must integrate your device with an email account using one of the following options.

BlackBerry Internet Service option

Use this option if one or more of the following situations apply:

- You purchased your device in a store.
- You want to set up a new email account for use with your device.
- You want to send and receive email messages on your device from one or more existing supported email accounts.

Note: To use this option, you must subscribe to a wireless service that supports email setup using BlackBerry Internet Service.

If this setup option applies to you, see "Setting up for email using BlackBerry Internet Service" on page 9 for more information.

BlackBerry Enterprise Server option

Use this option if all the following situations apply:

- A system administrator is managing a BlackBerry Enterprise Server™ within your company.
- A system administrator has confirmed that you are permitted to use the BlackBerry Enterprise Server.
- You want to receive messages from a corporate Microsoft® Outlook®, IBM® Lotus Notes®, or Novell® GroupWise® email account.

- Your supported email account resides on a Microsoft Exchange, IBM Lotus® Domino®, or Novell GroupWise email server.
- You subscribe to a wireless service that supports account setup using the BlackBerry Enterprise Server.

If this setup option applies to you, see "Setting up for email using BlackBerry Enterprise Server" on page 13 for more information.

Setting up for email using BlackBerry Internet Service

Create an account

You must create an account to begin using email on your BlackBerry device. The account that you create supplies the default email address for your device.

1. Verify that your device is connected to the wireless network and that you are in a wireless coverage area.

If the Sign In screen does not appear automatically, click **Email Settings**.

If you have problems, see "BlackBerry Internet Service - frequently asked questions" on page 21 for more information.

2. On the Sign In screen, click **Create Your Account**.

Note: To follow a link in the browser, click the link. Click **Get Link**.

3. Click **Continue**.
4. Read the legal terms and conditions carefully. Perform one of the following actions:
 - To decline the legal terms and conditions and stop the setup process, click **I Disagree**.
 - To accept the legal terms and conditions and continue the setup process, click **I Agree**.
5. Type your account information.
 - **User ID:** Type a personal user ID for your account. This user ID will be your login name and the first part of the default email address for your device.
 - **Friendly Name:** Type the name that you want to appear in the From field of messages that you send. If you do not

type a name, the default email address for your device appears in the From field.

- **Password:** Type a personal login password. Passwords must contain between 4 and 16 characters. Passwords are case sensitive and cannot contain accented characters.
- **Re-enter Password:** Retype your personal login password.

Note: Write down your user ID and password and keep the information in a safe place. You must type this information every time that you log in to your BlackBerry Internet Service account.

6. Select a secret question.

If you forget your password, you are prompted with this question.
7. Type an answer to your secret question.
8. Click **Submit**.
9. Click **Done**.
10. Perform one of the following actions:
 - To receive email on your device from other supported accounts, click **Add Account**. See "Receive messages from other email accounts" on page 10 for more information.
 - To log in to your account without adding other email accounts, click **Continue**.

Tip: If you have problems creating your account using your device, create your account using a desktop browser. See "Set account options" on page 11 for more information.

Log in to your account

Log in to your BlackBerry Internet Service account to manage settings and message options.

1. Verify that your device is connected to the wireless network and that you are in a wireless coverage area.
2. Click **Email Settings**.
3. On the Sign In screen, type your account information.
 - **User ID:** Type the login name for your account.
 - **Password:** Type the password for your account.
4. Click **Submit**.

Note: To follow a link in the browser, click the link. Click **Get Link**.

Receive messages from other email accounts

Set up your BlackBerry Internet Service account to retrieve messages from an existing supported email account and deliver them to your device. Add up to ten different existing supported accounts.

Note: Depending on your Internet service provider (ISP) or system administrator, you might not be able to add some types of accounts.

1. Verify that your device is connected to the wireless network and that you are in a wireless coverage area.
2. Log in to your BlackBerry Internet Service account. See "Log in to your account" on page 10 for more information.
3. Click **Add Account**.

Note: To follow a link in the browser, click the link. Click **Get Link**.

4. Type the information for the account that you want to add.
 - **Email Address:** Type the full email address of the account.
 - **User Name:** Type the login ID (for example, *kateturner* or *domain1kateturner*).
 - **Password:** Type the password.
 - **Re-enter Password:** Retype the password.
5. Click **Submit**.
6. Depending on the account that you add, you might be prompted to select an account type.
7. Depending on the account type that you select, you might be prompted for the following information:
 - **Email Server:** Type the messaging and collaboration server address for your Internet service provider (for example, *mail.ispname.com*). If you do not know the address, contact your Internet service provider.
 - **Port Number:** Type the appropriate port number. If you do not know the number, contact your Internet service provider.
 - **Outlook Web Access URL:** Type the web address for your Microsoft Outlook account.
 - **Mailbox Name:** Type the mailbox name for your Microsoft Outlook account.
 - **iNotes™ URL:** Type the web address for your IBM Lotus Notes account.
 - **Leave messages on mail server:** Clear this check box if you do not want to save messages that are sent to your device on the messaging server.

Note: If you delete a message from your device, you cannot recover it.

- **Utilize SSL:** Turn on Secure Sockets Layer encryption for retrieving messages from this account, if SSL is supported by your Internet service provider.

Note: If you add a corporate Microsoft Outlook or IBM Lotus Notes email account, you might be prompted to install the BlackBerry Mail Connector application on your computer. Complete the on-screen instructions. See "What is the BlackBerry Mail Connector?" on page 21 for more information.

8. Click **Submit**.

Set account options

Set additional account and message options by logging into your account using a desktop browser.

To access your account using a desktop browser, the following system requirements apply:

- **Internet browser:** Microsoft® Internet Explorer version 5.01, 5.5, or 6.0 (or later) or Netscape® Communicator version 4.08 to 4.58 with JavaScript™ enabled

Note: Netscape Communicator version 6 (or later) is not supported.

- **Operating system:** Microsoft® Windows® 95, Windows 98, Windows ME, Windows NT® (version 4), Windows 2000, Windows XP, or Mac OS® 9.0 or 10.0

1. In your desktop browser, type the web address provided by your wireless service provider.
2. Log in to your account.
3. Use this web site to set additional account options, which include
 - reactivating your account
 - changing your password

- creating an auto signature
- setting options for sent messages
- switching to a new device

See the *BlackBerry Internet Service Online Help* for more information about setting these options.

Install the BlackBerry Desktop Software

Install the BlackBerry Desktop Software to perform any of the following actions:

- synchronize personal information management (PIM) data such as contacts, tasks, and appointments
- backup and restore device data
- load new device programs such as updated system software, games, and third-party personal information management programs
- charge your device using your computer

To install the desktop software, the following system requirements apply:

- Intel®-compatible 486 or higher computer that is compliant with USB 1.1 or later
 - Windows®98, Windows ME, Windows 2000, or Windows XP
 - Available USB port
 - If you use Windows 98 (not Windows 98 Second Edition), you must download the DCOM 98 version 1.3 update from [www.microsoft.com/com/default.msp](http://www.microsoft.com/com/default.msp?x=US&y=US&lang=EN) for the USB driver to operate as expected.
1. Insert the BlackBerry Desktop Software Installation CD into your CD drive.
 2. Complete the on-screen instructions.
 - Select **BlackBerry Internet Service** as your account integration option.

3. When the installation is complete, connect the smaller end of the USB cable to your device.
4. Connect the larger end of the USB cable to an available USB port on your computer.
5. On the Windows taskbar, click **Start**.
6. Click **Programs > BlackBerry > Desktop Manager**.

Note: To find more information about the features of the BlackBerry Desktop Software, click **Help > Desktop Help Contents**.

Setting up for email using BlackBerry Enterprise Server

Your system administrator might set up your device for email on your behalf, or you might need to integrate your BlackBerry device with a supported email account yourself using one of the methods described here.

Use enterprise activation

If your system administrator has provided you with an enterprise activation password, you can integrate your supported email account directly from your device.

1. Verify that your device is connected to the wireless network and that you are in a wireless coverage area.
2. On your device, click **Enterprise Activation**.
3. Type your supported corporate email account address.
4. Type the enterprise activation password provided by your system administrator.
5. Click **Activate**.

Note: Your system administrator might request that you install the BlackBerry Device Manager program on your computer to reduce the amount of data that is sent over the wireless network when your device is connected to your computer.

Use the BlackBerry Desktop Software

If your system administrator does not provide you with an enterprise activation password, you can install the BlackBerry Desktop Software on your computer to integrate your device with your supported email account.

To install the desktop software, the following system requirements apply:

- Intel-compatible 486 or higher computer that is compliant with USB 1.1 or later

- Windows 98, Windows ME, Windows 2000, or Windows XP
 - Available USB port
 - If you use Windows 98 (not Windows 98 Second Edition), you must download the DCOM 98 version 1.3 update from www.microsoft.com/com/default.msp?for=usb for the USB driver to operate as expected.
1. Insert the BlackBerry Desktop Software Installation CD into your CD drive.
 2. Complete the on-screen instructions.
 - Select **BlackBerry Enterprise Server or BlackBerry Desktop Redirector** as your account integration option.
 - Select **BlackBerry Enterprise Server** as your email redirection option.
 3. When the installation is complete, connect the smaller end of the USB cable to your device.
 4. Connect the larger end of the USB cable to an available USB port on your computer.
 5. On the Windows taskbar, click **Start**.
 6. Select **Programs > BlackBerry > Desktop Manager**.
 - When you are prompted to generate an encryption key, complete the on-screen instructions.

Note: To find out more information about the features of the BlackBerry Desktop Software, click **Help > Desktop Help Contents**.

How do I...

Make phone calls

In the phone, type a phone number or select a contact.

Press the **Enter** key. To end the call, hold the **Escape** button.

Notes: If the contact that you want to call is not listed, click the trackwheel. Click **Call From Address Book** to select a contact from your address book.

You can also make a call on the Home screen. Type the number and press the **Enter** key.

Send email messages

You must set up a supported email account to use with your device before you can send and receive email messages. See "Choosing your email setup option" on page 7 for more information.

1. In the messages list, click the trackwheel.
2. Click **Compose Email**.
3. In the **To** field, type an email address or a contact name.
4. Type a message.
5. Click the trackwheel.
6. Click **Send**.

Note: If your device is integrated with more than one email account, you can select an account to send the message from. At the top of the message, in the **Send Using** field, press the **Space** key until the preferred email account appears.

Send PIN messages

A personal identification number (PIN) uniquely identifies each BlackBerry device on the network. If you know the PIN of another BlackBerry device user, you can send a PIN message to that person. To find your PIN, in the device options, click **Status**.

1. In the messages list, click the trackwheel.
2. Click **Compose PIN**.
3. In the **To** field, type a PIN or a contact name.
4. Type a message.
5. Click the trackwheel.
6. Click **Send**.

Send SMS (text) messages

1. In the messages list, click the trackwheel.
2. Click **Compose SMS**.
3. Click **[Use Once]**.
4. Click **SMS**.
5. Click **Phone**.
6. Type an SMS-compatible phone number.
7. Click the trackwheel.
8. Click **Continue**.
9. Type a message.
10. Click the trackwheel.
11. Click **Send**.

Send MMS (multimedia) messages

1. In the messages list, click the trackwheel.
2. Click **Compose MMS**.
3. Click **[Use Once]**.

4. Click **MMS**.
5. Select a send method for your MMS message.
6. Type an MMS-compatible phone number or an email address.
7. Click the trackwheel.
8. Click **Continue**.
9. Type a message.
10. Click the trackwheel.
11. Click **Attach Address, Attach Appointment, or Attach Picture**.
12. Click a contact, appointment, or image.
13. Click **Continue**.
14. Click the trackwheel.
15. Click **Send**.

Add contacts

1. In the address book, click the trackwheel.
2. Click **New Address**.
3. Type the contact information.
4. Click the trackwheel.
5. Click **Save**.

Add SIM card contacts to your address book

If you have saved contact information on your SIM card, you can copy that information into the address book on your device.

1. In the address book, click the trackwheel.
2. Click **SIM Phone Book**.
3. Click the trackwheel. Click **Copy All To Address Book**.

Go to web pages

1. In the browser, click the trackwheel.

2. Click **Go To**.
3. Type a web address.
4. Click the trackwheel.
5. Click **OK**.

Notes: To insert a period, press the **Space** key.

To insert a slash mark (/), press the **Shift** key + the **Space** key.

The **Go To** dialog box tracks the web addresses that you type. To go to a web page on the list, click the web address. Click **OK**.

Set a device password

1. In the device options, click **Security Options**.
2. Click **General Settings**.
3. Set the **Password** field to **Enabled**.
4. Set the other security options.
5. Click the trackwheel.
6. Click **Save**.
7. Type a device password.
8. Click the trackwheel.
9. Retype the device password.
10. Click the trackwheel.

Lock and unlock the device

With a device password set, on the Home screen, click **Lock**.

To unlock your device, on the Lock screen, roll the trackwheel. Click **Unlock**. Type your password. Press the **Enter** key.

Note: When the device is locked, you should be able to make an emergency call without dialing the emergency access number. Click **Emergency Call**. Click **Yes**.

Set the date and time

1. In the device options, click **Date/Time**.
2. Set the **Time Zone** field.
3. In the **Date/Time Source** field, set a date and time source.
4. Click the trackwheel.
5. Click **Update Time**.
6. Click the trackwheel.
7. Click **Save**.

Note: To set the date and time yourself, set the **Date/Time Source** field to **Off**. Set the other fields on the Date/Time screen to display the correct date and time. Save your changes.

Enable profiles

In the profiles list, click a notification profile. Click **Enable**.

Note: To change the current notification profile quickly, select a profile. Press the **Space** key.

Turn on or off the Bluetooth radio

To turn on the Bluetooth® radio, in the device options, click **Bluetooth**. Click the trackwheel. Click **Enable Bluetooth**.

To turn off the Bluetooth radio, in the device options, click **Bluetooth**. Click the trackwheel. Click **Disable Bluetooth**.

Pair with another Bluetooth-enabled device

1. In the device options, click **Bluetooth**.
2. Click the trackwheel.
3. Click **Add Device**.
4. Click the name of a Bluetooth-enabled device.

5. In the **Enter passkey for <device name>** field, type a passkey.
6. Type the same passkey on the Bluetooth-enabled device to which you are pairing.

Notes: Verify that the Bluetooth-enabled device that you want to pair with is in the correct mode for pairing.

The names of Bluetooth-enabled devices with which you have already paired appear in the list of paired Bluetooth-enabled devices. They do not appear in the list of Bluetooth-enabled devices that appears when you click **Add Device**.

Find help with other features

To access a list of topics that are associated with the program that you are using, in a program, click the trackwheel. Click **Help**.

To open the main list of topics for all programs, on any Help Screen, click the trackwheel. Click **Index**.

Frequently asked questions

Why does my device not turn on?

The power might be off. Press the **Power** button.

The battery might not be charged. See "Charge the battery" on page 5 for more information.

Why does my device not charge?

A connection might not be complete. Check that all cables and plugs are fully inserted into ports and power outlets. See "Charge the battery" on page 5 for more information.

The battery might not be inserted properly. Remove and reinsert the battery. Verify that the connectors align. See "Insert the battery" on page 5 for more information.

If you connect your device to the computer to charge, verify that the computer is turned on. If you connect your device to the computer using a USB hub, the hub must be self powered to provide enough power to charge your device.

Can I charge my device by connecting it to my computer?

If you have installed the BlackBerry Desktop Software or the BlackBerry Device Manager on your computer you can connect your device to the computer to charge the battery.

1. Verify that the computer is turned on.
2. Connect the smaller end of the USB cable to your device.
3. Connect the larger end of the USB cable to an available USB port on your computer.

Note: To find more help with connecting your device to the computer, in the desktop software, click **Help** to view the *BlackBerry Desktop Software Online Help*.

Why can I not send or receive email messages?

Verify that your device is connected to the wireless network and that you are in a wireless coverage area. See "Connect to the wireless network" on page 6 for more information.

Verify that you have set up a supported email account for use with your device. See "Choosing your email setup option" on page 7 for more information.

If you are using BlackBerry Internet Service, log in to your account using a desktop browser. See "Set account options" on page 11 for more information.

- Verify that your BlackBerry Internet Service account mailbox has not exceeded its size limit.
- Send a service book to reactivate your account.

If you continue to be unable to send and receive messages, reset your device by removing and reinserting the battery.

Note: To find more help with sending and receiving email messages, in messages list, click the trackwheel. Click **Help > Email Messages**.

Can I integrate my device with a corporate email account if I do not have access to a BlackBerry Enterprise Server?

If you use Microsoft Outlook (Workgroup installation) with an email account on a Microsoft Exchange Server version 5.5 or later and your device does not have access to a BlackBerry Enterprise Server, your system administrator might permit you to install the BlackBerry Desktop Redirector on your computer to integrate your device with your supported email account.

To integrate your device with a supported email account using the BlackBerry Desktop Redirector, when you install the BlackBerry Desktop Software, select **BlackBerry Desktop Redirector** as your message redirection option. See "Use the BlackBerry Desktop Software" on page 13 for more information about installing the BlackBerry Desktop Software.

Your computer must be on and the BlackBerry Desktop Redirector must be running to send and receive messages on your device.

Can I set up for email using both the BlackBerry Enterprise Server and BlackBerry Internet Service?

If your wireless service permits email setup using more than one service, complete the steps in "Setting up for email using BlackBerry Enterprise Server" on page 13 followed by the steps in "Setting up for email using BlackBerry Internet Service" on page 9.

Contact your service provider for more information about availability and the fees that might be associated with email setup using both BlackBerry Enterprise Server and BlackBerry Internet Service.

How do I reset my device?

To reset your device hardware and programs, remove and then reinsert the battery.

How do I clean the screen?

Clean the screen and device using only a soft dry cloth. Do not use liquid, aerosol cleaners, or solvents on or near your device. Disconnect any cables from the computer and unplug any charging accessories from the electrical outlet before cleaning.

Note: See the *BlackBerry Wireless Device Safety and Product Information* for more information about caring for your device.

Where can I buy accessories for my device?

You can buy approved accessories for your device online at:

www.shopblackberry.com

Note: Use only those accessories approved by Research In Motion (RIM) for use with your particular device model. Using any accessories not approved by RIM for use with your particular device model might invalidate any approval or warranty applicable to the device and might be dangerous.

Where can I download games and ring tones for my device?

Many third-party vendors offer games, ring tones, and other programs for your device online. You can download new programs using your device browser, or download them using your computer and load them onto your device using the Application Loader tool of the BlackBerry Desktop Software.

For example, you can visit the following web site using the browser on your device:

mobile.blackberry.com

Note: Your use of third party software shall be governed by and subject to you agreeing to the terms of separate software licenses, if any, for those products or services. Any third party products or services that are provided with RIM's products and services are provided "as is". RIM makes no representation, warranty or guarantee whatsoever in relation to the third party products or services and RIM assumes no liability whatsoever in relation to the third party products and services even if RIM has been advised of the possibility of such damages or can anticipate such damages.

Why can I not use shortcuts on the Home screen?

By default, you can quickly dial phone numbers from the Home screen. To use shortcuts on the Home screen, in the phone, click **Options**. Click **General Options**. Set the **Dial From Home Screen** field to **No**.

BlackBerry Internet Service - frequently asked questions

How do I open BlackBerry Internet Service?

See "Log in to your account" on page 10 for more information.

Why does the Email Settings option not appear on the Home screen?

Verify that your device is connected to the wireless network and that you are in a wireless coverage area. See "Connect to the wireless network" on page 6 for more information.

If your device uses a theme, the option might appear in a folder or list instead of on the Home screen. The option might also use a different name.

If the option still does not appear, contact your service provider.

What is the BlackBerry Mail Connector?

The BlackBerry Mail Connector is a program that you might have to install on your local computer to enable BlackBerry Internet Service to access your corporate Microsoft Outlook or IBM Lotus Notes email account when the corporate messaging server is behind a firewall.

The BlackBerry Mail Connector is designed to access and copy your messages that are on a messaging server and send them to BlackBerry Internet Service.

The BlackBerry Internet Service email account setup process is designed to automatically detect whether the BlackBerry Mail Connector is required and to prompt you to install the application.

Why can I not add a third-party email account?

Verify that the third-party email account supports POP3 or IMAP4. Contact your Internet service provider for more information about the account types that you can add.

How do I update my account information?

1. Log in to your BlackBerry Internet Service account. See "Log in to your account" on page 10 for more information.
2. Click **View/Modify**.
Note: To follow a link in the browser, click the link. Click **Get Link**.
3. Edit your account information.
4. Click **Submit**.

I use multiple accounts. How do I set the email address that appears in the From field of messages that I send?

1. Log in to your BlackBerry Internet Service account. See "Log in to your account" on page 10 for more information.
2. In the **Send From Address** option, click the **here** link.
Note: To follow a link in the browser, click the link. Click **Get Link**.
3. On the Sent From Address screen, perform one of the following actions:
 - To use your default BlackBerry Internet Service account as your Sent From Address, select **I want my Sent From Address to be my handheld email address**.
 - To use an address from one of the email accounts that you have added, select I

want to choose one of the email accounts I have set up to be my Sent From Address. Click **Submit**. Select an account.

- To use another email address, select **I want to customize my Sent From Address setting to use an email address that I'll enter**. Click **Submit**. Type the email address.
4. Click **Submit**.

How do I remove an account that I no longer want to access with my device?

1. Log in to your BlackBerry Internet Service account. See "Log in to your account" on page 10 for more information.
2. Select an email address.
Note: You cannot delete your default email account.
3. Click **Delete**.
Note: To follow a link in the browser, click the link. Click **Get Link**.
4. Click **Yes**.

How do I change the device that I want to use with my account?

Your account is linked to your particular device. If you switch devices, update the device PIN that is associated with your account, or call your service provider to delete your account.

1. Use your new device to log in to your BlackBerry Internet Service account. See "Log in to your account" on page 10 for more information.
2. Click **Change handheld that works with the accounts listed above**.

Note: To follow a link in the browser, click the link. Click **Get Link**.

3. On the Change Handheld screen, verify that the new device information is correct.
 - **PIN:** personal information number (PIN) for your device
 - **IMEI:** The international mobile equipment identity (IMEI) number for your device.**Note:** To find your PIN and IMEI, in the device options, click **Status**.
4. Click **Submit**.
5. Click **Done**.

Why is my mailbox full?

Your BlackBerry Internet Service account has a size limit. To avoid reaching the limit, delete items from your mailbox regularly or set up auto-aging rules for message deletion.

To view the available space in your mailbox or to set up auto-aging rules, log in to your BlackBerry Internet Service account. Click **Manage Folders**.

See the *BlackBerry Internet Service Online Help* for information on managing your account by deleting messages.

How do I find more information on managing my account?

Log in to your BlackBerry Internet Service account using a desktop browser. See "Log in to your account" on page 10 for more information.

See the *BlackBerry Internet Service Online Help* for more information on managing your account.

For additional BlackBerry help and troubleshooting information:

www.blackberry.com/support

© 2005 Research In Motion Limited. All Rights Reserved. The BlackBerry and RIM families of related marks, images and symbols are the exclusive properties of Research In Motion Limited. RIM, Research In Motion, 'Always On, Always Connected', the "envelope in motion" symbol and BlackBerry are registered with the U.S. Patent and Trademark Office and may be pending or registered in other countries.

The Bluetooth word mark and logos are owned by the Bluetooth SIG Inc. and any use of such marks by Research In Motion Limited is under license. IBM, Lotus Notes, Lotus, Domino, and iPhones are registered trademarks of International Business Machines Corporation in the United States and/or other countries. Intel is a registered trademark of Intel Corporation or its subsidiaries in the United States and other countries. JavaScript is a trademark of Sun Microsystems Inc. in the United States and other countries. Mac OS is a trademark of Apple Computer Inc. registered in the United States and other countries. Microsoft, Windows, Windows NT and Outlook are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries. Netscape is a registered trademark of Netscape Communication Corporation. Novell and GroupWise are registered trademarks of Novell Inc. in the United States and other countries. All other brands, product names, company names, trademarks, and service marks are the properties of their respective owners.

The BlackBerry device and/or associated software are protected by copyright, international treaties and various patents, including one or more of the following U.S. patents: 6,278,442; 6,271,605; 6,219,694; 6,075,470; 6,073,318; D445,428; D433,460; D416,256. Other patents are registered or pending in various countries around the world. Visit www.rim.com/patents.shtml for a current listing of applicable patents.

This document is provided "as is" and Research In Motion Limited and its affiliated companies ("RIM") assume no responsibility for any typographical, technical or other inaccuracies in this document. RIM reserves the right to periodically change information that is contained in this document; however, RIM makes no commitment to provide any such changes, updates, enhancements or other additions to this document to you in a timely manner or at all. RIM MAKES NO REPRESENTATIONS, WARRANTIES, CONDITIONS OR COVENANTS, EITHER EXPRESS OR IMPLIED (INCLUDING WITHOUT LIMITATION, ANY EXPRESS OR IMPLIED WARRANTIES OR CONDITIONS OF FITNESS FOR A PARTICULAR PURPOSE, NON-INFRINGEMENT, MERCHANTABILITY, DURABILITY, TITLE, OR RELATED TO THE PERFORMANCE OR NON-PERFORMANCE OF ANY SOFTWARE REFERENCED HEREIN OR PERFORMANCE OF ANY SERVICES REFERENCED HEREIN). IN CONNECTION WITH YOUR USE OF THIS DOCUMENTATION, NEITHER RIM NOR ITS RESPECTIVE DIRECTORS, OFFICERS, EMPLOYEES OR CONSULTANTS SHALL BE LIABLE TO YOU FOR ANY DAMAGES WHATSOEVER BE THEY DIRECT, ECONOMIC, COMMERCIAL, SPECIAL, CONSEQUENTIAL, INCIDENTAL, EXEMPLARY OR INDIRECT DAMAGES, EVEN IF RIM HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, INCLUDING WITHOUT LIMITATION, LOSS OF BUSINESS REVENUE OR EARNINGS, LOST DATA, DAMAGES CAUSED BY DELAYS, LOST PROFITS, OR A FAILURE TO REALIZE EXPECTED SAVINGS.

This document might contain references to third party sources of information, hardware or software, products or services and/or third party web sites (collectively the "Third-Party Information"). RIM does not control, and is not responsible for, any Third-Party Information, including, without limitation the content, accuracy, copyright compliance, compatibility, performance, trustworthiness, legality, decency, links, or any other aspect of Third-Party Information. The inclusion of Third-Party Information in this document does not imply endorsement by RIM of the Third Party Information or the third party in any way. Installation and use of Third Party Information with RIM's products and services may require one or more patent, trademark or copyright licenses in order to avoid infringement of the intellectual property rights of others. Any dealings with Third Party Information, including, without limitation, compliance with applicable licenses and terms and conditions, are solely between you and the third party. You are solely responsible for determining whether such third party licenses are required and are responsible for acquiring any such licenses relating to Third Party Information. To the extent that such intellectual property licenses may be required, RIM expressly recommends that you do not install or use Third Party Information until all such applicable licenses have been acquired by you or on your behalf. Your use of Third Party Information shall be governed by and subject to you agreeing to the terms of the Third Party Information licenses. Any Third Party Information that is provided with RIM's products and services is provided "as is". RIM makes no representation, warranty or guarantee whatsoever in relation to the Third Party Information and RIM assumes no liability whatsoever in relation to the Third Party Information even if RIM has been advised of the possibility of such damages or can anticipate such damages.

Check with your service provider for availability, roaming arrangements, service plans and features.

Certain features outlined in this document require a minimum version of BlackBerry Enterprise Server Software, BlackBerry Desktop Software, and/or BlackBerry Handheld Software and may require additional development or third-party products and/or services for access to corporate applications

BlackBerry 7290™
Model number: RAP40GW

Published in XXXXXX
PRINTSPEC-005

Where can I find more information?

User guide

The user guide is only a few clicks away on your device! To learn more about how to use your device, click **Help**.

In the menu on your device, click **Help** to see help topics associated with the program that you are using.

Additional resources

If you use the BlackBerry Internet Service™, log in to your account using a desktop browser. On the menu bar, click **Help** to view the *BlackBerry Internet Service Online Help*.

If you use the BlackBerry Desktop Software, on the menu bar click **Help** to find the *BlackBerry® Desktop Software Online Help* and the *BlackBerry User Guide*.